



## 1000DK83 Inverter & Battery Backup (1,000 watts 9.0 Amps)

Pure Sine Wave Inverter can be used to power (1 ea) single 1HP operator or (2 ea) 1/2HP operator.

- Low Battery Alarm: 10.5V
- Low Battery Shutdown: 9.5V
- Overload Protection
- Input Short Protection
- Over Temperature Control (140 F/ 60 C)
- LED Status Indicator
- Status Report Capability

- 1000 Watts of Cont. Power
- Max AC Load Current Mod. Sine Wave = 9.0A
- Max AC Load Current Pure Sine Wave = 12.5A
- DC Input: 10 to 15 VDC
- Nominal: 12 VDC
- Frequency: 60 Hz
- AC output voltage: 120 VAC

Battery:

(2 ea) Maintenance Free, Rechargeable, Non-Spillable, sealed lead acid (SLA) 12 Volt, 35.0AH Batteries wired in parallel.

